



POWER TRANSFORMERS


CHASSIS MOUNT - SINGLE SECONDARY



Case Type X



Case Type A



Case Type U

DESCRIPTION: MagneTek offers a full choice of TRIAD power supply transformers for direct use or in transformer, rectifier, or filter circuits. Other available secondary voltages include control, filament and low level signaling in standard values. The transformers are single primary with single and multiple secondaries in standard size and weight configurations.

SPECIFICATIONS:

Primary: 115/230 V, 50/60 Hz

Single Secondary

Case Type	Model	Primary	Secondary	Weight	Power	Mounting	Leads	Lead 1	Lead 2	Lead 3	Lead 4	Lead 5	Lead 6	Lead 7	Lead 8	Lead 9	Lead 10	Lead 11	Lead 12	Lead 13	Lead 14	Lead 15	Lead 16	Lead 17	Lead 18	Lead 19	Lead 20	Lead 21	Lead 22	Lead 23	Lead 24	Lead 25	Lead 26	Lead 27	Lead 28	Lead 29	Lead 30	Lead 31	Lead 32	Lead 33	Lead 34	Lead 35	Lead 36	Lead 37	Lead 38	Lead 39	Lead 40	Lead 41	Lead 42	Lead 43	Lead 44	Lead 45	Lead 46	Lead 47	Lead 48	Lead 49	Lead 50	Lead 51	Lead 52	Lead 53	Lead 54	Lead 55	Lead 56	Lead 57	Lead 58	Lead 59	Lead 60	Lead 61	Lead 62	Lead 63	Lead 64	Lead 65	Lead 66	Lead 67	Lead 68	Lead 69	Lead 70	Lead 71	Lead 72	Lead 73	Lead 74	Lead 75	Lead 76	Lead 77	Lead 78	Lead 79	Lead 80	Lead 81	Lead 82	Lead 83	Lead 84	Lead 85	Lead 86	Lead 87	Lead 88	Lead 89	Lead 90	Lead 91	Lead 92	Lead 93	Lead 94	Lead 95	Lead 96	Lead 97	Lead 98	Lead 99	Lead 100
A	F-1X#	2.5 CT	3.0	115	1,500	X	Leads	1 ¹ / ₈	2 ¹ / ₁₆	1 ¹ / ₈	2 ¹ / ₈	-	0.68																																																																																														
	F-301X	2.5 CT	3.0	115/230	1,500	X	Leads	1 ¹ / ₈	2 ¹ / ₁₆	1 ¹ / ₈	2 ¹ / ₈	-	0.68																																																																																														
	F-6X#	2.5 CT	6.0	115	2,500	X	Leads	1 ¹ / ₁₆	3 ¹ / ₁₆	1 ¹ / ₄	2 ¹ / ₁₆	-	1.0																																																																																														
	F-3X#	2.5 CT	10.0	115	3,000	X	Leads	2 ¹ / ₃₂	3 ¹ / ₄	2 ¹ / ₈	3 ¹ / ₈	-	1.7																																																																																														
B	F-7X	5.0 CT	3.0	115	1,500	X	Leads	1 ¹ / ₁₆	3 ¹ / ₁₆	2	2 ¹ / ₁₆	-	1.3																																																																																														
	F-8X	5.0 CT	6.0	115	1,500	X	Leads	2 ¹ / ₃₂	3 ¹ / ₄	2 ¹ / ₈	3 ¹ / ₈	-	1.7																																																																																														
	F-12X	5.0 CT	8.0	115	2,500	X	Leads	2 ¹ / ₃₂	4	2 ¹ / ₄	3 ¹ / ₁₆	-	2.5																																																																																														
C	F-13X	6.3	0.6	115	1,500	X	Leads	1 ¹ / ₈	2 ¹ / ₈	1 ¹ / ₈	2	-	0.37																																																																																														
	F-313X	6.3	0.6	115/230	1,500	X	Leads	1 ¹ / ₈	2 ¹ / ₈	1 ¹ / ₈	2	-	0.37																																																																																														
	F-14X#	6.3 CT	1.2	115	2,500	X	Leads	1 ¹ / ₈	2 ¹ / ₁₆	1 ¹ / ₈	2 ¹ / ₈	-	0.7																																																																																														
	F-314X	6.3 CT	1.2	115/230	2,500	X	Leads	1 ¹ / ₈	2 ¹ / ₁₆	1 ¹ / ₈	2 ¹ / ₈	-	0.7																																																																																														
	F-16X	6.3 CT	3.0	115	2,500	X	Leads	1 ¹ / ₁₆	3 ¹ / ₁₆	2	2 ¹ / ₁₆	-	1.3																																																																																														
	F-316X	6.3 CT	3.0	115/230	2,500	X	Leads	1 ¹ / ₁₆	3 ¹ / ₁₆	2	2 ¹ / ₁₆	-	1.3																																																																																														
	F-43X#	6.3	4.0	115	1,500	X	Leads	1 ¹ / ₁₆	3 ¹ / ₁₆	2	2 ¹ / ₁₆	-	1.25																																																																																														
	F-18X	6.3 CT	6.0	115	1,500	X	Leads	2 ¹ / ₃₂	4	2 ¹ / ₄	3 ¹ / ₁₆	-	2.3																																																																																														
	F-318X	6.3 CT	6.0	115/230	1,500	X	Leads	2 ¹ / ₃₂	4	2 ¹ / ₄	3 ¹ / ₁₆	-	2.3																																																																																														
	F-69X	6.3 CT	8.0	115	1,500	X	Leads	2 ¹ / ₁₆	4	2 ¹ / ₄	3 ¹ / ₁₆	-	2.3																																																																																														
	F-21A	6.3 CT	10.0	115	1,500	A	1-Leads	3 ¹ / ₃₂	2 ¹ / ₃₂	3 ¹ / ₈	2 ¹ / ₄	2	3.8																																																																																														
F-22A	6.3 CT	20.0	115	2,000	A	2-Leads	3 ¹ / ₈	3 ¹ / ₃₂	4 ¹ / ₈	2 ¹ / ₂	3	7.0																																																																																															
D	F-28U†	7.5 CT or 6.3 CT	25.0	115	3,000	U	Leads & Lugs	4 ¹ / ₈	3 ¹ / ₁₆	3 ¹ / ₈	3	3 ¹ / ₁₆	7.5																																																																																														
E	F-180X	10.0 CT	1.0	115	1,500	X	Leads	1 ¹ / ₁₆	3 ¹ / ₁₆	1 ¹ / ₄	2 ¹ / ₁₆	-	0.9																																																																																														
	F-31X	10.0 CT	3.0	115	2,000	X	Leads	2 ¹ / ₃₂	3 ¹ / ₄	2 ¹ / ₈	3 ¹ / ₈	-	1.7																																																																																														

60 Hz † Tapped primary to produce lower voltages CT = Center Tap
 Mounting hole sizes: X = 3/16" U = 13/64" x 3/8" A = 3/8" x 3/16"

POWER TRANSFORMERS

CHASSIS MOUNT - SINGLE SECONDARY



Single Secondary (cont'd)


30

Model	Primary	Secondary	W	H	W	W	W	W	W	W	W	W	W
A	F-96U	10.0 CT	6.0	115	1,500	U	Leads	3	2 1/2	2 3/4	2	2 5/16	2.1
	F-97U	10.0 CT	8.0	115	1,500	U	Leads	3 7/16	2 3/16	3	2 1/4	2 1/2	4.0
B	F-113X	12.0	0.15	115	1,500	X	Leads	1 3/8	2 1/8	1 3/8	2	-	0.4
	F-216X#	12.0	0.35	115	1,500	X	Leads	1 3/8	2 1/8	1 3/8	2	-	0.37
	F-114X	12.0	0.7	115	1,500	X	Leads	1 3/8	2 3/16	1 3/8	2 3/8	-	0.8
	F-217X#	12.0	1.2	115	1,500	X	Leads	2	3 1/4	1 3/4	2 13/16	-	1.0
	F-218X#	12.0	2.0	115	1,500	X	Leads	2	3 1/4	1 1/8	2 1/8	-	1.13
	F-219X#	12.0	4.0	115	1,500	X	Leads	2 7/16	4	2 1/4	3 3/16	-	2.3
	F-220U#	12.0	6.0	115	1,500	U	Leads	3 7/16	2 13/16	2 1/2	2 1/4	2 1/8	3.5
	F-221U#	12.0	8.0	115	1,500	U	Leads	3 3/16	3 1/8	2 7/8	2 1/2	2 1/8	4.0
C	F-29U†	12.0 CT or 11.0 CT or 10.0 CT	11.0	115	3,000	U	Leads	4 3/8	3 1/2	3 3/8	2 3/4	2 3/16	6.5
D	F-70X	12.6 CT	1.0	115	1,500	X	Leads	1 13/16	3 3/16	1 1/4	2 13/16	-	1.3
	F-25X	12.6 CT	1.5	115	1,500	X	Leads	1 13/16	3 3/16	2	2 13/16	-	1.3
	F-325X	12.6 CT	1.5	115/230	1,500	X	Leads	1 13/16	3 3/16	2	2 13/16	-	1.3
	F-44X#	12.6 CT	2.0	115	1,500	X	Leads	1 13/16	3 3/16	2	2 13/16	-	1.25
	F-344X	12.6 CT	2.0	115/230	1,500	X	Leads	1 13/16	3 3/16	2	2 13/16	-	1.25
	F-26X#	12.6 CT	2.5	115	1,500	X	Leads	2 7/32	3 1/16	2	3 1/8	-	1.55
	F-326X	12.6 CT	2.5	115/230	1,500	X	Leads	2 7/32	3 1/16	2	3 1/8	-	1.55
	F-224X#	12.6	3.0	115	1,500	X	Leads	2 1/4	3 3/4	2 1/8	3 1/8	-	1.6
	F-225X#	12.6	4.0	115	1,500	X	Leads	2 7/8	4	2 1/16	3 3/16	-	2.3
	F-3181U	12.6 CT	4.0	115/230	1,500	U	Leads	3 1/16	2 7/16	2 1/16	2	2	2.3
	F-182U	12.6 CT	6.0	115	1,500	U	Leads	3 3/8	2 3/16	2 1/16	2 1/4	2 3/8	3.8
	F-183U	12.6 CT	8.0	115	1,500	U	Leads	3 3/16	3 3/16	2 13/16	2 1/2	2 1/4	5.0
E	F-112X	14.0 CT	0.25	115	1,500	X	Leads	1 3/8	2 3/8	1 3/8	2	-	0.4
	F-3112X	14.0 CT	0.25	115/230	1,500	X	Leads	1 3/8	2 3/8	1 1/2	2	-	0.3
	F-250X	14.0 CT	1.0	115	1,500	X	Leads	1 13/16	3 3/4	1 3/4	2 13/16	-	1.2
	F-251X	14.0 CT	2.0	115	1,500	X	Leads	2 1/4	3 3/16	1 13/16	3 3/8	-	1.5
	F-252U	14.0 CT	4.0	115	1,500	U	Leads	3	2 1/2	2 7/16	2	2 1/4	3.0
	F-253U	14.0 CT	6.0	115	1,500	U	Leads	3 3/8	2 3/16	2 7/8	2 1/4	2 3/4	4.0
F	F-254X	20.0 CT	1.0	115	1,500	X	Leads	2 1/4	3 1/16	1 5/16	3 3/8	-	1.5
	F-255X	20.0 CT	2.0	115	1,500	X	Leads	2 7/16	4	2 1/4	3 3/16	-	2.5
	F-256U	20.0 CT	4.0	115	1,500	U	Leads	3 3/8	2 7/16	2 7/8	2 3/8	-	4.0
	F-257U	20.0 CT	6.0	115	1,500	U	Leads	3 3/4	3 1/8	3 3/8	2 1/2	2 7/8	5.7
	F-258U	20.0 CT	8.0	115	1,500	U	Leads	3 3/4	3 1/8	3 1/2	2 1/2	2 7/8	6.4
	F-259U	20.0 CT	10.0	115	1,500	U	Leads	4 1/8	3 1/8	3 1/2	2 1/4	2 3/4	7.4
G	F-115X	24.0 CT	0.085	115	1,500	X	Leads	1 3/8	2 1/16	1 3/8	1 3/4	-	0.3
	F-3115X	24.0 CT	0.085	115/230	1,500	X	Leads	1 3/16	2 1/16	1 3/8	1 3/4	-	0.3
	F-116X	24.0 CT	0.2	115	1,500	X	Leads	1 3/8	2 3/8	1 1/2	2	-	0.45
	F-3116X	24.0 CT	0.2	115/230	1,500	X	Leads	1 3/8	2 3/8	1 1/2	2	-	0.45
	F-117X	24.0 CT	0.4	115	1,500	X	Leads	1 3/8	2 13/16	1 3/8	2 3/8	-	0.8
	F-3117X	24.0 CT	0.4	115/230	1,500	X	Leads	1 3/8	2 13/16	1 1/2	2 3/8	-	0.75
	F-118X	24.0 CT	0.7	115	1,500	X	Leads	2	3 1/4	2	2 13/16	-	1.3
	F-3118X	24.0 CT	0.7	115/230	1,500	X	Leads	2	3 1/4	2	2 13/16	-	1.3
	F-45X#	24.0 CT	1.0	115	1,500	X	Leads	1 13/16	3 3/16	2	2 13/16	-	1.3
	F-345X	24.0 CT	1.0	115/230	1,500	X	Leads	1 13/16	3 3/16	2	2 13/16	-	1.3
	F-46X#	24.0	1.0	115	1,500	X	Leads	1 5/16	3 1/4	2 1/8	2 13/16	-	1.4
	F-229X#	24.0	2.0	115	1,500	X	Leads	2 1/16	4	2	3 3/16	-	2.3
	F-192X	24.0 CT	2.0	115	1,500	X	Leads	2 19/32	4	2 1/4	3 3/16	-	2.3
	F-193U	24.0 CT	4.0	115	1,500	U	Leads	3 11/16	3 3/8	2 13/16	2 1/2	2 1/4	4.0
	F-260U	24.0 CT	6.0	115	1,500	U	Leads	3 3/4	3 3/8	3 1/2	2 1/2	2 7/8	6.4
	F-261U	24.0 CT	8.0	115	1,500	U	Leads	4 1/8	3 1/16	3 1/2	2 3/4	2 3/4	7.4
F-401U	24.0 CT	10.0	115	1,500	U	Leads	4 1/8	3 1/16	3 3/4	2 3/4	3	8.0	
F-226U#	24.0 CT	12.0	115	1,500	U	Leads	4 7/16	3 3/4	4 1/8	3	3 1/4	10.4	


60 Hz † Tapped primary to produce lower voltages CT = Center Tap
 Mounting hole sizes: U = 1 3/16" x 3/16" X = 3/16"

POWER TRANSFORMERS


CHASSIS MOUNT - SINGLE SECONDARY



Case Type X



Case Type U



Case Type Z

Single Secondary (cont'd)

Section	Type No.	Secondary		Primary Voltage	RMS Test Voltage (Sec.)	Case Type	Connections	Dimensions			Mounting Dimensions		Wt. Lbs.
		Volts	Amps					H	W	D	MW	MD	
A	F-57X	25.2 CT	1.0	117	1,500	X	Leads	1 ¹⁵ / ₁₆	3 ³ / ₁₆	2	2 ¹³ / ₁₆	-	1.5
	F-357X	25.2 CT	1.0	115/230	1,500	X	Leads	1 ¹⁵ / ₁₆	3 ³ / ₁₆	2	2 ¹³ / ₁₆	-	1.5
	F-41X#	25.2 CT	2.0	115	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.2
	F-341X	25.2 CT	2.0	115/230	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.2
	F-56X	25.2 CT	2.8	115	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.5
B	F-119X	26.8 CT	0.15	115	1,500	X	Leads	1 ³ / ₈	2 ³ / ₈	1 ¹ / ₂	2	-	0.45
	F-40X#	26.8 CT	1.0	115	1,500	X	Leads	1 ¹⁵ / ₁₆	3 ³ / ₁₆	2	2 ¹³ / ₁₆	-	1.3
	F-340X	26.8 CT	1.0	115/230	1,500	X	Leads	1 ¹⁵ / ₁₆	3 ³ / ₁₆	2	2 ¹³ / ₁₆	-	1.3
	F-55X	26.8 CT	1.7	115	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.3
	F-355X	26.8 CT	1.7	115/230	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.3
C	F-122X	28.0 CT	0.175	115	1,500	X	Leads	1 ³ / ₈	2 ³ / ₈	1 ¹ / ₂	2	-	0.35
	F-124X	28.0 CT	0.8	115	1,500	X	Leads	1 ¹⁵ / ₁₆	3 ³ / ₁₆	2	2 ¹³ / ₁₆	-	1.0
	F-184X	28.0 CT	1.0	115	1,500	X	Leads	2 ⁷ / ₁₆	3 ¹ / ₁₆	2 ¹ / ₄	3 ³ / ₁₆	-	1.4
	F-3185U	28.0 CT	2.0	115/230	1,500	X	Leads	3 ⁷ / ₁₆	2 ¹ / ₂	2 ¹ / ₁₆	2	2 ¹ / ₄	2.9
	F-187U	28.0 CT	4.0	115	1,500	U	Leads	3 ¹ / ₂	2 ³ / ₈	3 ¹ / ₁₆	2 ¹ / ₄	2 ¹ / ₄	5.3
D	F-188X	35.0 CT	0.1	115	1,500	X	Leads	1 ³ / ₈	2 ¹³ / ₁₆	1 ¹ / ₁₆	2 ³ / ₈	-	0.35
	F-228X#	35.0 CT	0.3	115	1,500	X	Leads	1 ³ / ₈	2 ¹³ / ₁₆	1 ¹ / ₁₆	2 ³ / ₈	-	0.6
	F-189X	35.0 CT	0.5	115	1,500	X	Leads	2 ⁷ / ₁₆	3 ¹ / ₁₆	1 ¹³ / ₁₆	3 ³ / ₁₆	-	1.0
	F-54X	35.0 CT	1.5	115	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.2
	F-354X	35.0 CT	1.5	115/230	1,500	X	Leads	2 ¹³ / ₃₂	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.2
	F-191U	35.0 CT	4.0	115	1,500	U	Leads	3 ¹³ / ₁₆	3 ³ / ₁₆	3 ³ / ₁₆	2 ¹ / ₄	2 ¹ / ₂	6.0
E	F-268U	35.0 CT	8.0	115	1,500	U	Leads	4 ¹ / ₂	3 ³ / ₄	4 ¹ / ₄	3	3 ³ / ₄	11.0
	F-270X	40.0 CT	1.0	115	1,500	X	Leads	2 ⁹ / ₁₆	4	2 ¹ / ₄	3 ³ / ₁₆	-	2.6
	F-271U	40.0 CT	2.0	115	1,500	U	Leads	3 ³ / ₈	2 ¹³ / ₁₆	2 ³ / ₈	2 ¹ / ₄	2 ³ / ₈	4.0
	F-272U	40.0 CT	4.0	115	1,500	U	Leads	3 ³ / ₄	3 ³ / ₈	3 ¹ / ₂	2 ¹ / ₂	2 ³ / ₈	6.4
	F-273U	40.0 CT	6.0	115	1,500	U	Leads	4 ¹ / ₂	3 ³ / ₄	4	3	3	10.0
F	F-275U	40.0 CT	10.0	115	1,500	U	Leads	5 ³ / ₈	4 ⁷ / ₈	4 ¹ / ₂	3 ¹ / ₂	3 ³ / ₈	14.5
	F-59X	60.0 CT	0.4	115	1,500	X	Leads	1 ¹⁵ / ₁₆	3 ³ / ₁₆	2	2 ¹³ / ₁₆	-	1.3
	F-279U	60.0 CT	1.0	115	1,500	U	Leads	3	2 ¹ / ₂	2 ⁵ / ₈	2	2 ³ / ₈	3.4
	F-280U	60.0 CT	2.0	115	1,500	U	Leads	3 ³ / ₄	3 ³ / ₈	3 ³ / ₈	2 ¹ / ₂	2 ³ / ₈	5.6
F-282U	60.0 CT	6.0	115	1,500	U	Leads	5 ¹ / ₄	4 ³ / ₈	4 ¹ / ₈	3 ¹ / ₂	2 ³ / ₈	12.5	

60 Hz CT = Center Tap Mounting hole sizes: X = ³/₁₆" U = ¹³/₁₆" x ³/₁₆"

Multiple Secondary

Section	Type No.	Secondary		Primary Voltage	RMS Test Voltage (Sec.)	Case Type	Connections	Dimensions			Mounting Dimensions		Wt. Lbs.
		Volts	Amps					H	W	D	MW	MD	
G	F-235Z#	12.0 CT	0.25	115	1,500	Z	Lugs	2	2 ³ / ₈	1 ¹ / ₁₆	2	-	0.6
	F-236Z#	12.0 CT	0.25	115	1,500	Z	Lugs	2 ⁷ / ₁₆	2 ¹ / ₄	1 ⁵ / ₈	2 ³ / ₈	-	0.9
	F-237Z#	12.0 CT	0.5	115	1,500	Z	Lugs	2 ⁷ / ₁₆	2 ¹ / ₄	1 ⁵ / ₈	2 ³ / ₈	-	1.1
	F-237Z#	12.0 CT	1.0	115	1,500	Z	Lugs	2 ⁷ / ₁₆	2 ¹³ / ₁₆	2 ¹ / ₁₆	2 ³ / ₈	-	1.1
H	F-241U#f	18.0 CT	1.0	115	1,500	U	Lugs	2 ¹ / ₂	3	2 ¹ / ₂	2 ¹ / ₂	2	2.2
	F-243U#f	18.0 CT	1.0	115	1,500	U	Lugs	3 ¹ / ₂	4 ¹ / ₈	3 ¹ / ₄	3 ³ / ₁₆	2 ¹ / ₄	5.2
	F-244U#f	18.0 CT	4.0	115	1,500	U	Lugs	3 ¹ / ₂	4 ¹ / ₈	3 ¹ / ₄	3 ³ / ₁₆	2 ¹ / ₄	5.2
	F-244U#f	18.0 CT	4.0	115	1,500	U	Lugs	3 ¹ / ₂	4 ¹ / ₈	3 ¹ / ₄	3 ³ / ₁₆	2 ¹ / ₄	5.2
I	F-195X	32.0 CT	0.250	115	1,500	X	Leads	2 ¹ / ₄	3 ³ / ₄	1 ⁷ / ₈	3 ³ / ₈	-	1.3
	F-195X	15.5 CT	0.750	115	1,500	X	Leads	2 ¹ / ₄	3 ³ / ₄	1 ⁷ / ₈	3 ³ / ₈	-	1.3
J	F-196U	32.0 CT	1.0	115	1,500	U	Leads	3 ³ / ₈	2 ¹³ / ₁₆	2 ³ / ₈	2 ¹ / ₄	2 ¹ / ₄	4.0
	F-196U	15.0 CT	2.0	115	1,500	U	Leads	3 ³ / ₈	2 ¹³ / ₁₆	2 ³ / ₈	2 ¹ / ₄	2 ¹ / ₄	4.0
K	F-197U	32.0 CT	1.0	115	1,500	U	Leads	3 ³ / ₄	3 ³ / ₈	2 ¹³ / ₁₆	2 ¹ / ₂	2 ¹ / ₄	4.7
	F-197U	15.0 CT	4.0	115	1,500	U	Leads	3 ³ / ₄	3 ³ / ₈	2 ¹³ / ₁₆	2 ¹ / ₂	2 ¹ / ₄	4.7
L	F-198U	32.0 CT	1.0	115	1,500	U	Leads	3 ³ / ₄	3 ³ / ₈	3 ³ / ₁₆	2 ¹ / ₂	2 ¹ / ₄	6.2
	F-198U	15.0 CT	6.0	115	1,500	U	Leads	3 ³ / ₄	3 ³ / ₈	3 ³ / ₁₆	2 ¹ / ₂	2 ¹ / ₄	6.2

f Windings may be connected in series to obtain their combined voltage when properly phased. Current will be equal to the current of the lowest winding. Example: Two 6.3 V windings @ 2A in series would be 12.6 V @ 2A. Windings may also be connected in parallel to obtain combined current. Example: Two 6.3 V windings @ 2A in parallel would be 6.3 V @ 4A.

60 Hz CT = Center Tap Mounting hole sizes: X = ³/₁₆" U = ¹³/₁₆" x ³/₁₆" Z = ³/₁₆"

