



44 FARRAND STREET
BLOOMFIELD, NJ 07003
(973) 748-5089

NTE1433 Integrated Circuit Audio Preamp

Description:

The NTE1433 is a linear integrated circuit in a 7-Lead SIP type package designed for use in high voltage preamplification applications.

Features:

- Power Supply with Wide Working Voltage Range (20–42 Volts)
- High Open Loop Gain
- Extremely Low Distortion
- Low Noise
- High Input Impedance and Low Output Impedance
- Low Current Dissipation

Application:

- Stereos Radios & Tape Recorders

Absolute Maximum Ratings:

Supply Voltage, V_{CC}	42V
Supply Current, I_{CC}	5mA
Operating Temperature Range, T_{opr}	-25° to +75°C
Storage Temperature Range, T_{stg}	-55° to +125°C

Electrical Characteristics:

Parameter	Symbol	Test Conditions	Min	Typ	Max	Unit
Open Loop Voltage Gain	G_{VO}		82	90	—	dB
Max Output Voltage	V_{om}	$KF = 0.1\%$, R_{IAA}	7.5	9.0	—	V_{rms}
Supply Current	I_{cc}	$V_{OUT} = 0$	—	3.5	—	mA
Output Noise Voltage	V_{NO}	$R_g = 2.2k\Omega$, R_{IAA}	—	100	150	μV_{rms}
Input Noise Voltage	V_{NI}	$R_g = 2.2k$ R_{IAA}	—	1.0	1.5	μV_{RMS}
Total Harmonic Distortion	THD	$V_{OUT} = 5V_{rms}$, R_{IAA}	—	0.03	—	%
Input Impedance	Z_{in}	$G_{VC} = 40dB$, R_{IAA}	—	130	—	$k\Omega$
Output Impedance	Z_{out}	$G_{VC} = 40dB$, R_{IAA}	—	12	—	Ω

Pin Connection Diagram
(Front View)

