

### SAKS 1

Fuse cartridge, 5 x 20/5 x 25




### SAKS 4

Fuse cartridge, E14/D 01  
(e.g. Neozed D 01)



### SAKS 6

Fuse cartridge, 11/4" x 1/4"  
to DEF 63



### SAKS 7

Fuse cartridge, 5 x 20/5 x 25



#### Warning:

In the event of a faulty fuse, the connected circuit has a leakage current flow equal to the indicator current specified.

Dimensions						
Terminal width (+ 0.2 assembly tolerance)	mm	13	24	13	12	
Insulation stripping length	mm	12	14	12	12	
<b>Connection data</b>						
Screw connection, flexible		0.5...10mm <sup>2</sup>	0.5...10mm <sup>2</sup>	0.5...10mm <sup>2</sup>	0.5...10mm <sup>2</sup>	
Wire size		#20...8 AWG	#20...6 AWG	#20...8 AWG	#20...8 AWG	
<b>VDE rated data</b>						
Current		10A	16A	10A	10A	
LED current (24...60 V)		≤ 5mA	-	-	-	
LED current (115...230 V)		-	-	-	-	
Incandescent lamp current		≤ 50mA	-	-	-	
Neon lamp current		≤ 0.5mA	≤ 1mA	≤ 1mA	≤ 1mA	
Cross-section		10mm <sup>2</sup>	10mm <sup>2</sup>	10mm <sup>2</sup>	10mm <sup>2</sup>	
<b>Ordering data</b>			<b>Type</b>	<b>Cat. No.</b>	<b>Type</b>	
<b>Fuse cartridge</b>			<b>SAKS 4</b>		<b>SAKS 6 KrG</b>	
<b>5 x 20</b>	LED	24VDC	SAKS 1 LD		53182	
		24VAC	37142	22582		
		48VDC	111122	111132		
		48VAC	12172	22602		
	Incandescent lamp	24VAC/DC	21392	21402		
		48VAC	SAKS 1 GL			
			37172	17322		
			37892	17312		
	Neon lamp	115VAC/DC	SAKS 1 GL			
		230VAC/DC	38532			
<b>Fuse cartridge</b>	LED	24VDC	SAKS 1 LD			
			40782	on request		
			SAKS GL			
			38802	on request		
	Incandescent lamp	24VAC/DC	38812	on request		
		48VAC	SAKS 1 GL			
	Neon lamp	115VAC/DC	38522	-		
		230VAC/DC	30932	19862		
	<b>Accessories</b>		<b>Type</b>	<b>Cat. No.</b>	<b>Type</b>	<b>Cat. No.</b>
	Mounting rail		TS 32	12280	TS 32	12280
		TS 35x7.5	38340			
		TS 35x15	49800			
End bracket (thickness mm)	for TS 32	EWK 1 (8.5)	20616	EWK 1 (8.5)	20616	
	for TS 35	EW 35 (8.5)	38356			
End plate (thickness mm)		AP KrG (3)	19132	AP KrG	14672	
Jumpering brackets				QL 2	19140	
Type "QL"				QL 3	19150	
				QL 4	19160	
				QL 10	33880	
Fixing screw (matches QL)				BS M 3x6 w. SS	34620	
Screw cap (spare)		SK (5 x 20)	28210			
		SK (5 x 25)	28200			
Neon lamp				Neon lamp 230VAC	55030	
				Neon lamp 115VAC	55020	
				Neon lamp 230VAC	55030	
				Neon lamp 11VAC	55020	