

# Attenuators

## SMA Subminiature "MINIPAD"®

### Hex Body Types - High Performance

DC - 26.5 GHz Hex Body 298HEX Series Model Numbers		
Male/Female	Female/Female	Male/Male
ATT-0298-XX-HEX-02	ATT-298F-XX-HEX-02	ATT-298M-XX-HEX-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		



DC - 18.0 GHz Hex Body 290HEX Series Model Numbers		
Male/Female	Female/Female	Male/Male
ATT-0290-XX-HEX-02	ATT-290F-XX-HEX-02	ATT-290M-XX-HEX-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		

### SPECIFICATIONS - HIGH PERFORMANCE

**Attenuation Accuracy:** 1-6 dB  $\pm$  0.3 dB  
7-20 dB  $\pm$  0.5 dB  
21-30 dB  $\pm$  1.0 dB

**VSWR:** 1.07+.015(f GHz) max

**Power:** 2 Watts Average @ +25 °C derated linearly to .5 watts @ +125 °C and 200 Watts peak

**Operating Temperature Range:** -65 °C to +125 °C


**Finish:** Passivated Stainless Steel

DC - 12.4 GHz Hex Body 291HEX Series Model Numbers		
Male/Female	Female/Female	Male/Male
ATT-0291-XX-HEX-02	ATT-291F-XX-HEX-02	ATT-291M-XX-HEX-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		




Attenuation Value	Length A
1-12 dB	0.86
13-30 dB	1.02

DC - 8.0 GHz Hex Body 292HEX Series Model Numbers		
Male/Female	Female/Female	Male/Male
ATT-0292-XX-HEX-02	ATT-292F-XX-HEX-02	ATT-292M-XX-HEX-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		



Attenuation Value	Length A
1-12 dB	0.90
13-30 dB	1.03

DC - 2.0 GHz Hex Body 294HEX Series Model Numbers		
Male/Female	Female/Female	Male/Male
ATT-0294-XX-HEX-02	ATT-294F-XX-HEX-02	ATT-294M-XX-HEX-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		



Attenuation Value	Length A
1-12 dB	0.98
13-30 dB	1.12

# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

## Emerson Connectivity Solutions:

[ATT-0290-00-HEX-02](#) [ATT-0290-01-HEX-02](#) [ATT-0290-02-HEX-02](#) [ATT-0290-03-HEX-02](#) [ATT-0290-04-HEX-02](#)  
[ATT-0298-18-HEX-02](#) [ATT-0298-19-HEX-02](#) [ATT-0298-20-HEX-02](#) [ATT-0298-30-HEX-02](#) [ATT-0298-12-HEX-02](#)  
[ATT-0298-13-HEX-02](#) [ATT-0298-14-HEX-02](#) [ATT-0298-15-HEX-02](#) [ATT-0298-16-HEX-02](#) [ATT-0298-17-HEX-02](#)  
[ATT-0298-06-HEX-02](#) [ATT-0298-07-HEX-02](#) [ATT-0298-08-HEX-02](#) [ATT-0298-09-HEX-02](#) [ATT-0298-10-HEX-02](#)  
[ATT-0298-11-HEX-02](#) [ATT-0294-30-HEX-02](#) [ATT-0298-01-HEX-02](#) [ATT-0298-02-HEX-02](#) [ATT-0298-03-HEX-02](#)  
[ATT-0298-04-HEX-02](#) [ATT-0298-05-HEX-02](#) [ATT-0294-07-HEX-02](#) [ATT-0294-08-HEX-02](#) [ATT-0294-09-HEX-02](#)  
[ATT-0294-10-HEX-02](#) [ATT-0294-15-HEX-02](#) [ATT-0294-20-HEX-02](#) [ATT-0292-30-HEX-02](#) [ATT-0294-01-HEX-02](#)  
[ATT-0294-02-HEX-02](#) [ATT-0294-03-HEX-02](#) [ATT-0294-04-HEX-02](#) [ATT-0294-05-HEX-02](#) [ATT-0292-07-HEX-02](#)  
[ATT-0292-08-HEX-02](#) [ATT-0292-09-HEX-02](#) [ATT-0292-10-HEX-02](#) [ATT-0292-15-HEX-02](#) [ATT-0292-20-HEX-02](#)  
[ATT-0292-01-HEX-02](#) [ATT-0292-02-HEX-02](#) [ATT-0292-03-HEX-02](#) [ATT-0292-04-HEX-02](#) [ATT-0292-05-HEX-02](#)  
[ATT-0292-06-HEX-02](#) [ATT-0291-08-HEX-02](#) [ATT-0291-09-HEX-02](#) [ATT-0291-10-HEX-02](#) [ATT-0291-15-HEX-02](#)  
[ATT-0291-20-HEX-02](#) [ATT-0291-30-HEX-02](#) [ATT-0291-02-HEX-02](#) [ATT-0291-03-HEX-02](#) [ATT-0291-04-HEX-02](#)  
[ATT-0291-05-HEX-02](#) [ATT-0291-06-HEX-02](#) [ATT-0291-07-HEX-02](#) [ATT-0290-76-HEX-02](#) [ATT-0290-77-HEX-02](#)  
[ATT-0290-78-HEX-02](#) [ATT-0290-80-HEX-02](#) [ATT-0291-00-HEX-02](#) [ATT-0291-01-HEX-02](#) [ATT-0290-70-HEX-02](#)  
[ATT-0290-71-HEX-02](#) [ATT-0290-72-HEX-02](#) [ATT-0290-73-HEX-02](#) [ATT-0290-74-HEX-02](#) [ATT-0290-75-HEX-02](#)  
[ATT-0290-17-HEX-02](#) [ATT-0290-18-HEX-02](#) [ATT-0290-19-HEX-02](#) [ATT-0290-20-HEX-02](#) [ATT-0290-25-HEX-02](#)  
[ATT-0290-30-HEX-02](#) [ATT-0290-11-HEX-02](#) [ATT-0290-12-HEX-02](#) [ATT-0290-13-HEX-02](#) [ATT-0290-14-HEX-02](#)  
[ATT-0290-15-HEX-02](#) [ATT-0290-16-HEX-02](#) [ATT-0290-05-HEX-02](#) [ATT-0290-06-HEX-02](#) [ATT-0290-07-HEX-02](#)  
[ATT-0290-08-HEX-02](#) [ATT-0290-09-HEX-02](#) [ATT-0290-10-HEX-02](#)