

Attenuators

SMA Miniature Type

DC - 18 GHz High Performance

- DC-2, DC-4, DC-8, and DC-12.4 units available
- 0 - 60 dB Attenuation Values
- Rugged Stainless Steel Construction
- Any Male/Female combination available
- Low cost alternatives available

Midwest Microwave's SMA miniature series of fixed coaxial attenuators provide temperature stable, ruggedly built, precision performance in a small light weight package size. Attenuation values up through 60 dB in 1 dB increments are available with any of the units described and with any combination of female or male SMA connectors.



SPECIFICATIONS - HIGH PERFORMANCE

Frequency: DC - 18.0, DC - 12.4, DC - 8.0 GHz
DC - 4.0, DC - 2.0 GHz

Attenuation Accuracy: 1-10 dB ± 0.3 dB
11-20 dB ± 0.5 dB
21-40 dB ± 1.0 dB
41-60 dB ± 1.5 dB

VSWR: 1.07+.015 (f GHz) max.

Power: 2 Watts Average @ 25C derated linearly to .5 Watts @ 125C

Peak Power: 200 Watts

Operating Temperature Range: - 65 to + 125C

Finish: Passivated Stainless Steel

DC - 18 GHz	263 Series	Model Numbers
Male/Female	Female/Female	Male/Male
ATT-0263-XX-SMA-02	ATT-263F-XX-SMA-02	ATT-263M-XX-SMA-02
XX = Attenuation Value: Select 01-60dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		



Attenuation Value	Length A
1-20 dB	1.20
21-60 dB	1.49

DC - 12.4 GHz	205 Series	Model Numbers
Male/Female	Female/Female	Male/Male
ATT-0205-XX-SMA-02	ATT-205F-XX-SMA-02	ATT-205M-XX-SMA-02
XX = Attenuation Value: Select 01-60dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		



Attenuation Value	Length A
1-20 dB	1.07
21-60 dB	1.36

DC - 8.0 GHz	206 Series	Model Numbers
Male/Female	Female/Female	Male/Male
ATT-0206-XX-SMA-02	ATT-206F-XX-SMA-02	ATT-206M-XX-SMA-02
XX = Attenuation Value: Select 01-60dB in 1dB increments (.5 dB increments available)		
<i>HIGH PERFORMANCE</i>		



Attenuation Value	Length A
1-20 dB	1.33
21-60 dB	1.62

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Emerson Connectivity Solutions:

[ATT-263F-03-SMA-02](#) [ATT-263F-06-SMA-02](#) [ATT-263F-10-SMA-02](#) [ATT-263F-20-SMA-02](#) [ATT-263M-05-SMA-02](#)
[ATT-263M-06-SMA-02](#) [ATT-0263-75-SMA-02](#) [ATT-0263-76-SMA-02](#) [ATT-0263-77-SMA-02](#) [ATT-0263-78-SMA-02](#)
[ATT-0263-79-SMA-02](#) [ATT-0263-80-SMA-02](#) [ATT-0263-30-SMA-02](#) [ATT-0263-70-SMA-02](#) [ATT-0263-71-SMA-02](#)
[ATT-0263-72-SMA-02](#) [ATT-0263-73-SMA-02](#) [ATT-0263-74-SMA-02](#) [ATT-0263-15-SMA-02](#) [ATT-0263-16-SMA-02](#)
[ATT-0263-17-SMA-02](#) [ATT-0263-18-SMA-02](#) [ATT-0263-19-SMA-02](#) [ATT-0263-20-SMA-02](#) [ATT-0263-09-SMA-02](#)
[ATT-0263-10-SMA-02](#) [ATT-0263-11-SMA-02](#) [ATT-0263-12-SMA-02](#) [ATT-0263-13-SMA-02](#) [ATT-0263-14-SMA-02](#)
[ATT-0263-03-SMA-02](#) [ATT-0263-04-SMA-02](#) [ATT-0263-05-SMA-02](#) [ATT-0263-06-SMA-02](#) [ATT-0263-07-SMA-02](#)
[ATT-0263-08-SMA-02](#) [ATT-0205-15-SMA-02](#) [ATT-0205-20-SMA-02](#) [ATT-0205-30-SMA-02](#) [ATT-0263-00-SMA-02](#)
[ATT-0263-01-SMA-02](#) [ATT-0263-02-SMA-02](#) [ATT-0205-04-SMA-02](#) [ATT-0205-05-SMA-02](#) [ATT-0205-06-SMA-02](#)
[ATT-0205-08-SMA-02](#) [ATT-0205-09-SMA-02](#) [ATT-0205-10-SMA-02](#) [ATT-263M-10-SMA-02](#) [ATT-0205-00-SMA-02](#)
[ATT-0205-01-SMA-02](#) [ATT-0205-02-SMA-02](#) [ATT-0205-03-SMA-02](#)