

HA5006

General Description

The HA5006 is a C-band power amplifier which covers the frequencies from 5.3 to 5.9 GHz with a gain of 43 dB and an output power of 10 Watts.

The amplifier uses a single supply voltage, is DC regulated and has reverse polarity protection and over heat protection.

Electrical Performance

Typical Data @25 °C

Parameter	Min	Typ	Max	Units
Frequency Range	5.3		5.9	GHz
Small Signal Gain		43.0		dB
Gain Flatness		± 1	± 1.5	dB
Power Output@P _{1dB}	+40	+41		dBm
Input VSWR		1.5 : 1	2 : 1	
Output VSWR		1.5 : 1	2 : 1	
Temperature Range	0		+55	°C
DC Voltage	11.5	12.0	13.0	V
DC Current		5		A
Connectors	SMA female			
Package	tbd			
Size (without heat sink)	130 x 70 x 25			mm

Note: Cold plate required.

Rev. 1.0