

Attenuators

SMA Subminiature "MINIPAD"®

DC - 26.5 GHz High Performance

- DC-2, DC-8, DC-12.4, and DC-18 GHz units available
- Rugged Stainless Steel Construction
- Any Male/Female combination available
- Low cost alternatives available

Midwest Microwave's SMA subminiature series of fixed coaxial attenuators (MINIPAD®) provide temperature stable, ruggedly built, precision performance in a compact light weight package size. Attenuation values up through 30 dB in 1 dB increments are available with any of the units described and with any combination of female or male SMA connectors.

SPECIFICATIONS - HIGH PERFORMANCE

Frequency: DC - 18.0, DC - 12.4, DC - 8.0 GHz
DC - 4.0, and DC - 2.0 GHz

Attenuation Accuracy: 1-6 dB ± 0.3dB
7-20 dB ± 0.5 dB
21-30 dB ± 1.0 dB

VSWR: 1.07+.015 (f GHz) max.

Power: 2 Watts Average @ +25°C derated linearly to .5 watts @ +125°C

Peak Power: 200 Watts


Operating Temperature Range: -65 to +125C

Finish: Passivated Stainless Steel




TYPE II LOW VSWR - HIGH PERFORMANCE IMPROVED SPECIFICATIONS


Frequency GHz	VSWR
DC - 4.0 GHz	1.12 max
4.0 - 8.0 GHz	1.15 max
8.0 - 18 GHz	1.20 max



Attenuation Value	Length A
1-12 dB	0.86
13-30 dB	1.02



Attenuation Value	Length A
1-12 dB	0.90
13-30 dB	1.03



Attenuation Value	Length A
1-12 dB	0.98
13-30 dB	1.12

DC - 26.5 GHz	298 Series	Model Numbers
Male/Female	Female/Female	Male/Male
ATT-0298-XX-SMA-02	ATT-298F-XX-SMA-02	ATT-298M-XX-SMA-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
HIGH PERFORMANCE		

DC - 18 GHz	290 Series	Model Numbers
Male/Female	Female/Female	Male/Male
ATT-0290-XX-SMA-02	ATT-290F-XX-SMA-02	ATT-290M-XX-SMA-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
HIGH PERFORMANCE		

DC - 12.4 GHz	291 Series	Model Numbers
Male/Female	Female/Female	Male/Male
ATT-0291-XX-SMA-02	ATT-291F-XX-SMA-02	ATT-291M-XX-SMA-02
XX = Attenuation Value: Select 01-30dB in 1dB increments (.5 dB increments available)		
HIGH PERFORMANCE		

Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

Emerson Connectivity Solutions:

[ATT-290F-00-SMA-02](#) [ATT-290F-01-SMA-02](#) [ATT-290F-02-SMA-02](#) [ATT-290F-03-SMA-02](#) [ATT-290F-04-SMA-02](#)
[ATT-290F-05-SMA-02](#) [ATT-0298-19-SMA-02](#) [ATT-0298-20-SMA-02](#) [ATT-0298-30-SMA-02](#) [ATT-0298-16-SMA-02](#)
[ATT-0298-17-SMA-02](#) [ATT-0298-18-SMA-02](#) [ATT-0298-11-SMA-02](#) [ATT-0298-12-SMA-02](#) [ATT-0298-13-SMA-02](#)
[ATT-0298-14-SMA-02](#) [ATT-0298-15-SMA-02](#) [ATT-0298-04-SMA-02](#) [ATT-0298-05-SMA-02](#) [ATT-0298-06-SMA-02](#)
[ATT-0298-07-SMA-02](#) [ATT-0298-08-SMA-02](#) [ATT-0298-09-SMA-02](#) [ATT-0291-15-SMA-02](#) [ATT-0291-20-SMA-02](#)
[ATT-0291-30-SMA-02](#) [ATT-0298-01-SMA-02](#) [ATT-0298-02-SMA-02](#) [ATT-0298-03-SMA-02](#) [ATT-0291-05-SMA-02](#)
[ATT-0291-06-SMA-02](#) [ATT-0291-07-SMA-02](#) [ATT-0291-08-SMA-02](#) [ATT-0291-09-SMA-02](#) [ATT-0291-10-SMA-02](#)
[ATT-0290-80-SMA-02](#) [ATT-0291-00-SMA-02](#) [ATT-0291-01-SMA-02](#) [ATT-0291-02-SMA-02](#) [ATT-0291-03-SMA-02](#)
[ATT-0291-04-SMA-02](#) [ATT-0290-74-SMA-02](#) [ATT-0290-75-SMA-02](#) [ATT-0290-76-SMA-02](#) [ATT-0290-77-SMA-02](#)
[ATT-0290-78-SMA-02](#) [ATT-0290-79-SMA-02](#) [ATT-0290-25-SMA-02](#) [ATT-0290-30-SMA-02](#) [ATT-0290-70-SMA-02](#)
[ATT-0290-71-SMA-02](#) [ATT-0290-72-SMA-02](#) [ATT-0290-73-SMA-02](#) [ATT-0290-15-SMA-02](#) [ATT-0290-16-SMA-02](#)
[ATT-0290-17-SMA-02](#) [ATT-0290-18-SMA-02](#) [ATT-0290-19-SMA-02](#) [ATT-0290-20-SMA-02](#) [ATT-0290-09-SMA-02](#)
[ATT-0290-10-SMA-02](#) [ATT-0290-11-SMA-02](#) [ATT-0290-12-SMA-02](#) [ATT-0290-13-SMA-02](#) [ATT-0290-14-SMA-02](#)
[ATT-0290-03-SMA-02](#) [ATT-0290-04-SMA-02](#) [ATT-0290-05-SMA-02](#) [ATT-0290-06-SMA-02](#) [ATT-0290-07-SMA-02](#)
[ATT-0290-08-SMA-02](#) [ATT-290M-10-SMA-02](#) [ATT-290M-20-SMA-02](#) [ATT-290M-30-SMA-02](#) [ATT-0290-00-SMA-02](#)
[ATT-0290-01-SMA-02](#) [ATT-0290-02-SMA-02](#) [ATT-290M-04-SMA-02](#) [ATT-290M-05-SMA-02](#) [ATT-290M-06-SMA-02](#)
[ATT-290M-07-SMA-02](#) [ATT-290M-08-SMA-02](#) [ATT-290M-09-SMA-02](#) [ATT-290F-20-SMA-02](#) [ATT-290F-30-SMA-02](#)
[ATT-290M-00-SMA-02](#) [ATT-290M-01-SMA-02](#) [ATT-290M-02-SMA-02](#) [ATT-290M-03-SMA-02](#) [ATT-290F-06-SMA-02](#)
[ATT-290F-07-SMA-02](#) [ATT-290F-08-SMA-02](#) [ATT-290F-09-SMA-02](#) [ATT-290F-10-SMA-02](#)